




# Standard Maintenance schedule B Type 4



© INNIO Jenbacher GmbH & Co OG  
Achenseestr. 1-3  
A-6200 Jenbach, Austria  
[www.innio.com](http://www.innio.com)

**Maintenance instruction highlighted in green**

The maintenance instructions highlighted in green in the maintenance schedule are plant-specific and are incorporated into the customer-specific maintenance schedule according to engine type and version.

**Revision history**

Index	Date	Description / Revision summary	Expert <i>Auditor</i>
1	02.09.2019	First issue	<b>Technology</b> <i>Technology</i>

**The target recipients of this document are:**

Service Partners, commissioning partners, subsidiaries/branches, Jenbach location

**INNIO proprietary information: CONFIDENTIAL**

The information contained in this document is the proprietary information of INNIO Jenbacher GmbH & Co OG and its subsidiaries and is disclosed in confidence. It is the property of INNIO and shall not be used, disclosed to others or reproduced without express written consent. This includes but is not limited to use for the creation, manufacture, development or derivation of any repairs, modifications, spare parts, designs or configuration changes, or for obtaining government or regulatory approval to do so. If consent is given for reproduction in whole or in part, this notice and the notice set forth on each page of this document shall appear in any such reproduction in whole or in part.

**UNCONTROLLED WHEN PRINTED OR TRANSMITTED ELECTRONICALLY**

**Note to warranty claims:**

Complying with TA 1100-0113 ensures a safe, quick and proper execution of every maintenance task.

The risk assessment to be performed by the plant operator and the official and quasi-official safety rules and laws may give rise to acceptance tests, inspections and maintenance operations which are not included in the Maintenance Plan. The operator is responsible for implementing and enforcing these additional measures.

The maintenance intervals are based on empirical values during average types of operation while fully complying with the manufacturer's operating and maintenance instructions. In individual cases, the operating conditions and other factors relating to wear may affect the actual amount of maintenance required. The manufacturer therefore reserves the right to specify different maintenance intervals where appropriate.

**NOTE****Damage to the engine**

Damage to the engine may result if the intervals in the maintenance schedule are not followed precisely. Observe intervals related to the condition and starts, or intervals not to the operating hours.

The maintenance instructions highlighted in colour in the maintenance schedule are plant-specific and are incorporated into the customer-specific maintenance schedule according to engine type and version.

inspect	Wear parts and tolerances will be evaluated by INNIO and / or a company selected and authorized by INNIO, and may be changed as required as part of preventive maintenance. Seals require replacement due to disassembly of components for inspection.
replace	Indicates a scheduled preventive part exchange based on operating hours, time or starts.
overhaul	Parts will be disassembled, overhauled (cleaned, wear parts changed etc.) and assembled again.
c (condition-based)	The inspect-, replace-, and overhaul interval is condition based.
s (start-dependent)	The inspect-, replace-, and overhaul interval is start dependent.
t (time-dependent)	The inspect-, replace-, and overhaul interval is time dependent.
z (Thermal cycle)	The inspection, replacement or overhaul interval depends on the thermal cycle. A thermal cycle is defined as heating up to operating temperature and then cooling down to a defined temperature for the component in question. If the operating temperature is reached again before cooling down to below the limit temperature has taken place, there is no thermal cycle.
K	This activity is to be carried out by the customer, INNIO or a company selected and authorised by INNIO to carry out this work.
INNIO	This activity is to be carried out by INNIO or a company selected by INNIO authorised to carry out this work.
WA	Reference for the maintenance instruction.
I	A maintenance instruction which contains only inspection working tasks.
W	A maintenance instruction which contains only replacement / overhaul working tasks.
IW	A maintenance instruction which contains inspection and replacement / overhaul working tasks.
Oh	Operating hours



The line in the maintenance plan after the maintenance <100 Oh is shown as thicker. This line marks the difference between one-off intervals or intervals not related to operating hours, and intervals which have to be repeated after a certain number of operating hours.

The detailed **description of the time-, start- and condition-based intervals** can be found in the chapter maintenance interval in the respective **maintenance instruction**.

If a maintenance step depends on two different factors, for example operating hours and starts, the maintenance step need only be carried out once when a limit value is reached. After the maintenance step has been carried out, both limit values start counting again from the beginning.

Arbeitsschritte

		c	t	s	< 100 Oh	every 1.000 Oh	8,000 Oh	2,000 Oh	4,000 Oh	6,000 Oh	8,000 Oh	10,000 Oh	12,000 Oh	14,000 Oh	15,000 Oh	16,000 Oh	18,000 Oh	20,000 Oh	21,000 Oh	22,000 Oh	24,000 Oh	26,000 Oh	28,000 Oh	30,000 Oh	32,000 Oh	34,000 Oh	36,000 Oh	38,000 Oh	40,000 Oh	41,000 Oh	42,000 Oh	44,000 Oh	45,000 Oh	46,000 Oh	48,000 Oh	50,000 Oh	52,000 Oh	54,000 Oh	56,000 Oh	58,000 Oh	60,000 Oh						
Daily inspection	I 9003 0																																														
⇒ Inspecting the system		■																																													
Leak test	IW 8049 0																																														
⇒ Carrying out the leak test		■						■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■	■	■	■	
Inspection	I 0103 4																																														
⇒ Checking engine connection in myPlant								■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■	■	■	■	
⇒ Heat exchanger exhaust gas / water: Measuring the differential pressure								■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■	■	■	■	
⇒ Crankcase ventilation: Measuring the differential pressure								■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■	■	■	■	■
⇒ Thermal reactor: Measuring the differential pressure									■		■		■			■		■			■		■		■		■		■		■		■			■		■		■		■		■		■	
⇒ Flexibly-mounted coupling housing: Recording data									■		■		■			■		■			■		■		■		■		■		■		■			■		■		■		■		■		■	
⇒ Heat exchanger mixture / water: Measuring the differential pressure												■						■							■				■								■							■		■	
Maintenance after initial commissioning	W 1000 4																																														
⇒ Measuring the valve-stem projection					■																																										
⇒ Checking valve clearance					■																																										
⇒ Checking the ignition voltage					■																																										
⇒ Checking the thermal reactor (optional)					■																																										
⇒ Inspecting the flexibly-mounted coupling housing					■																																										
⇒ Inspecting the gas filter					■																																										
⇒ Lubricating the control rod linkage					■																																										
Surge arrestor in the Junction Box	IW 8029 A0																																														
⇒ Checking and cleaning the surge arrestor		■																																													
⇒ Measuring capacitance		■																																													
⇒ Replacing the unit		■																																													
Jenbacher Control cabinet	IW 8031 A0																																														
⇒ Replace the rubber buffer and filter mat		■																■											■																■		■
⇒ Inspect and clean filter fan including filter mat								■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■	■	■	■	■
⇒ Inspect and clean the interior of the control cabinet																		■											■																■		■
⇒ Inspect and clean the cooling device for the control cabinet																		■											■																■		■
Container	IW 8040 A0																																														
⇒ Replacing the container intake air filter		■																																													
⇒ Checking the louvre shutters			■																																												
⇒ Tightening the bolted joints			■																																												
Surge arrestor	IW 8047 A0																																														

Arbeitsschritte

		c	t	s	< 100 Oh	every 1.000 Oh	8,000 Oh	2,000 Oh	4,000 Oh	6,000 Oh	8,000 Oh	10,000 Oh	12,000 Oh	14,000 Oh	15,000 Oh	16,000 Oh	18,000 Oh	20,000 Oh	21,000 Oh	22,000 Oh	24,000 Oh	26,000 Oh	28,000 Oh	30,000 Oh	32,000 Oh	34,000 Oh	36,000 Oh	38,000 Oh	40,000 Oh	41,000 Oh	42,000 Oh	44,000 Oh	45,000 Oh	46,000 Oh	48,000 Oh	50,000 Oh	52,000 Oh	54,000 Oh	56,000 Oh	58,000 Oh	60,000 Oh						
⇒ Checking the surge arrester	IW 8047 A0		■																																												
Overvoltage deflector	IW 8048 A0																																														
⇒ Checking the overvoltage deflector			■																																												
Condensate removal in the fuel gas system	IW 8090 A0																																														
⇒ Manual condensate drain: Drain off condensate		■																																													
⇒ Automatic condensate removal: Check for leaks			■					■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■	■	■		
Exhaust gas system condensate drain line	IW 8095 A0																																														
⇒ Inspecting the condensate drain line in the exhaust gas system		■																																													
Generator	W 8030 A0																																														
⇒ Relubricating the bearing(s)		■							■		■		■			■		■			■		■		■		■		■			■				■		■		■		■		■		■	
⇒ Measuring the insulation/polarisation		■										■						■							■					■								■					■		■		
⇒ Daily check			■																																												
⇒ Inspecting and cleaning the generator												■						■							■				■									■					■		■		
⇒ Carrying out a vibration measurement and replacing the earth brush (if fitted)												■						■							■				■									■					■		■		
⇒ Replacing the bearing(s)																		■												■														■		■	
⇒ Overhauling the generator																															■														■		■
Generator	W 8032 A0																																														
⇒ Relubricating the bearing(s)		■						■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■	■	■	■	
⇒ Measuring the insulation/polarisation		■										■						■							■					■									■					■		■	
⇒ Replacing the bearing(s)		■																■											■															■		■	
⇒ Daily check			■																																												
⇒ Inspecting and cleaning the generator												■						■							■				■									■					■		■		
⇒ Carrying out a vibration measurement and replacing the earth brush (if fitted)												■						■							■				■									■					■		■		
⇒ Overhauling the generator																																													■		■
Generator	W 8034 A0																																														
⇒ Relubricating the bearing(s)		■				■																																									
⇒ Measuring the insulation/polarisation		■										■						■							■					■								■						■		■	
⇒ Daily check			■																																												
⇒ Inspecting and cleaning the generator												■						■							■				■									■					■		■		
⇒ Carrying out a vibration measurement and replacing the earth brush (if fitted)												■						■							■				■									■					■		■		
⇒ Replacing the bearing(s)																			■											■														■		■	
⇒ Overhauling the generator																																													■		■
Generator	W 8035 A0																																														

Arbeitsschritte

c- Condition-dependent

t- Time-dependent

s- Start-dependent

		c- Condition-dependent t- Time-dependent s- Start-dependent																																																											
		c	t	s	< 100 Oh	every 1.000 Oh	8,000 Oh	2,000 Oh	4,000 Oh	6,000 Oh	8,000 Oh	10,000 Oh	12,000 Oh	14,000 Oh	15,000 Oh	16,000 Oh	18,000 Oh	20,000 Oh	21,000 Oh	22,000 Oh	24,000 Oh	26,000 Oh	28,000 Oh	30,000 Oh	32,000 Oh	34,000 Oh	36,000 Oh	38,000 Oh	40,000 Oh	41,000 Oh	42,000 Oh	44,000 Oh	45,000 Oh	46,000 Oh	48,000 Oh	50,000 Oh	52,000 Oh	54,000 Oh	56,000 Oh	58,000 Oh	60,000 Oh																				
⇒ Relubricating the bearing(s)	W 8035 A0	■				■																																																							
⇒ Measuring the insulation/polarisation		■										■							■																								■																		
⇒ Daily check			■																																																										
⇒ Inspecting and cleaning the generator													■							■																							■																		
⇒ Carrying out a vibration measurement and replacing the earth brush (if fitted)													■							■																							■																		
⇒ Replacing the bearing(s)																				■																								■																	
⇒ Overhauling the generator																																												■																	
Generator		W 8037 A0																																																											
⇒ Relubricating the bearing(s)	■								■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■	■	■	■														
⇒ Measuring the insulation/polarisation	■												■						■						■																			■																	
⇒ Replacing the bearing(s)	■																		■																									■																	
⇒ Daily check			■																																																										
⇒ Inspecting and cleaning the generator														■						■																							■																		
⇒ Carrying out a vibration measurement and replacing the earth brush (if fitted)														■						■																								■																	
⇒ Overhauling the generator																																													■																
Plate heat exchanger	W 8043 A0																																																												
⇒ Replace the O-rings and rubber seals		■	■																																									■																	
⇒ Overhauling the plate heat exchanger																																													■																
Gas train	W 8045 A0																																																												
⇒ Inspect the gas filter and replace if necessary			■						■		■		■			■		■			■		■		■		■		■			■				■		■			■			■																	
⇒ Overhauling the gas train			■																																									■																	
⇒ Inspecting the gas train													■						■						■					■															■																
⇒ Overhauling the gas pressure controller/gas regulator																									■																			■																	
⇒ Overhauling the prechamber differential pressure controller																										■																		■																	
⇒ Overhauling the zero pressure controller (optional)																										■																			■																
Flat-bed cooler	W 8065 A0																																																												
⇒ Inspecting the fan power unit			■																																																										
⇒ Inspecting the fan bearing			■																																																										
⇒ Inspecting the fans			■																																																										
⇒ Inspecting the fan blades			■																																																										
Activated carbon adsorber	W 8074 A0																																																												
⇒ Flushing the activated carbon adsorber		■																																																											
⇒ Checking the activated carbon mass		■																																																											

Arbeitsschritte

		c- Condition-dependent				t- Time-dependent				s- Start-dependent																																				
		c	t	s	< 100 Oh	every 1.000 Oh	8,000 Oh	2,000 Oh	4,000 Oh	6,000 Oh	8,000 Oh	10,000 Oh	12,000 Oh	14,000 Oh	15,000 Oh	16,000 Oh	18,000 Oh	20,000 Oh	21,000 Oh	22,000 Oh	24,000 Oh	26,000 Oh	28,000 Oh	30,000 Oh	32,000 Oh	34,000 Oh	36,000 Oh	38,000 Oh	40,000 Oh	41,000 Oh	42,000 Oh	44,000 Oh	45,000 Oh	46,000 Oh	48,000 Oh	50,000 Oh	52,000 Oh	54,000 Oh	56,000 Oh	58,000 Oh	60,000 Oh					
⇒ Emptying and filling the activated carbon	W 8074 A0	■																																												
Cooling water	W 8080 A0																																													
⇒ Cooling water analysis		■	■					■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■	■	■	■
⇒ Replacing the cooling water		■																																												
⇒ Checking the water pressure			■																																											
⇒ Replacing O-rings			■															■												■														■		
⇒ Replace hoses			■															■												■														■		
In-line air filter	IW 8040 A4																																													
⇒ Replace filter cartridges		■									■					■					■				■					■							■				■					
⇒ Replace rubber buffers			■															■												■														■		
Flexibly-mounted coupling housing and engine mounting	IW 8079 A4																																													
⇒ Replace rubber elements on the coupling housing			■															■												■														■		
⇒ Replace rubber coupling element			■															■												■														■		
⇒ Replace the rubber rails of the engine and generator			■																						■																			■		
⇒ Measure the axial offset								■		■		■			■		■			■		■		■		■		■		■		■		■		■		■		■		■		■		
⇒ Inspect the rubber rails of the engine and generator																		■												■														■		
Humidity sensor	W 8048 A4																																													
⇒ Calibrating the EE330 humidity sensor, part no. 674941		■	■																																											
⇒ Replacing the PMA humidity sensor, part no. 9028765			■																																											
⇒ Replacing the EE220 humidity sensor tip, part no. 1243222			■																																											
Engine cooling water pump	W 0203 A6								■		■		■			■		■			■		■		■		■		■			■				■		■		■		■		■		■
⇒ Relubricating the bearings (only for pumps with grease nipples)																																														
⇒ Replacing the mechanical seal												■						■							■				■									■						■		
⇒ Overhauling the engine cooling water pump																									■																				■	
Camshaft/valve timing gear	IW 8052 M0																																													
⇒ Inspecting the camshaft																																													■	
⇒ Replacing roller tappets or cup tappets																																													■	
Combustion chamber	IW 8056 M0																																													
⇒ Inspecting and cleaning the combustion chamber		■																																												
⇒ Checking the fuel gas quality, in particular the silicon content for landfill gas engines			■																																											
⇒ Checking the oil consumption			■																																											
⇒ Check for oil ingress into the engine due to a faulty blow-by filter and inspect the intake line for "Oil wetness"			■																																											



Arbeitsschritte

		c	t	s	< 100 Oh	every 1.000 Oh	8,000 Oh	2,000 Oh	4,000 Oh	6,000 Oh	8,000 Oh	10,000 Oh	12,000 Oh	14,000 Oh	15,000 Oh	16,000 Oh	18,000 Oh	20,000 Oh	21,000 Oh	22,000 Oh	24,000 Oh	26,000 Oh	28,000 Oh	30,000 Oh	32,000 Oh	34,000 Oh	36,000 Oh	38,000 Oh	40,000 Oh	41,000 Oh	42,000 Oh	44,000 Oh	45,000 Oh	46,000 Oh	48,000 Oh	50,000 Oh	52,000 Oh	54,000 Oh	56,000 Oh	58,000 Oh	60,000 Oh			
⇒ Optimising the engine	IW 8056 M0											■						■							■					■							■						■	
⇒ Cleaning the combustion chamber															■										■								■										■	
<b>NOx</b>	IW 8057 M0																																											
⇒ Measure NOx value and if necessary adjust LEANOX setting		■					■	■	■	■	■		■			■			■	■	■	■	■		■		■				■	■	■		■	■		■		■				■
⇒ Replacing the NOx sensor (if present)										■			■				■				■			■			■				■					■			■				■	
<b>Control rod assembly/throttle valve/actuator</b>	W 0200 M0																																											
⇒ Inspecting and relubricating the control rod assembly								■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■			■	■	■	■	■	■	■	■	■	■
⇒ Inspect throttle valve								■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■			■	■	■	■	■	■	■	■	■	■
⇒ Replacing and lubricating pivot point, replacing throttle valve bearing												■						■							■					■							■						■	
⇒ Replacing throttle valve																		■											■														■	
⇒ Replacing the final controlling device, control lever and throttle valve shaft																								■																		■		
<b>Ignition</b>	W 0303 M0																																											
⇒ Cleaning the pick-ups								■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■			■	■	■	■	■	■	■	■	■	■
⇒ Replacing the spark plug connector gasket										■			■				■				■				■			■			■					■			■				■	
⇒ Inspecting the ignition system											■					■					■				■				■							■				■				
<b>Vibration damper</b>	W 0601 M0																																											
⇒ Replacing the vibration damper																		■												■													■	
<b>Mixture bypass valve</b>	W 0802 M0																																											
⇒ Mixture bypass valve – replacement																		■											■														■	
<b>Revision</b>	W 2100 M0																																											
⇒ Replacing the rubber rails of the engine and generator			■																																									■
⇒ Replacing the camshaft																																												■
⇒ Inspecting the crankshaft																																												■
⇒ Inspecting the crankcase																																												■
⇒ Inspecting the gear train																																												■
⇒ Inspecting the cylinder heads																																												■
⇒ Replacing piston, piston rings and piston pins																																												■
⇒ Replacing a cylinder liner																																												■
⇒ Replacing the crankshaft main bearings/crankshaft thrust bearings																																												■
⇒ Replacing big-end bearing shells																																												■
⇒ Replacing the vibration damper																																												■
<b>Exhaust-gas turbocharger</b>	W 8023 M0																																											

Arbeitsschritte

		c	t	s	< 100 Oh	every 1.000 Oh	8,000 Oh	2,000 Oh	4,000 Oh	6,000 Oh	8,000 Oh	10,000 Oh	12,000 Oh	14,000 Oh	15,000 Oh	16,000 Oh	18,000 Oh	20,000 Oh	21,000 Oh	22,000 Oh	24,000 Oh	26,000 Oh	28,000 Oh	30,000 Oh	32,000 Oh	34,000 Oh	36,000 Oh	38,000 Oh	40,000 Oh	41,000 Oh	42,000 Oh	44,000 Oh	45,000 Oh	46,000 Oh	48,000 Oh	50,000 Oh	52,000 Oh	54,000 Oh	56,000 Oh	58,000 Oh	60,000 Oh			
⇒ Inspecting the compressor side of the exhaust-gas turbocharger	W 8023 M0	■																																										
⇒ Replacing the O-rings			■									■							■						■											■					■			
⇒ Overhauling the exhaust-gas turbocharger													■						■						■												■					■		
⇒ Replacing the exhaust-gas turbocharger																																											■	
Exhaust-gas turbocharger	W 8025 M0																																											
⇒ Inspecting the compressor side of the exhaust-gas turbocharger		■																																										
⇒ Check that all the bolted joints/seals and covers sit properly.								■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■	
⇒ Overhauling the exhaust-gas turbocharger													■						■						■												■					■		
⇒ Replacing O-rings													■						■						■												■					■		
⇒ Replacing the impeller																									■																		■	
Starter motor	W 8032 M0																																											
⇒ Replacing the starter motor				■									■					■							■					■							■						■	
Piston	W 8047 M0																																											
⇒ Replace piston, piston rings and piston pins		■																	■										■														■	
⇒ Overhaul the piston cooling nozzles		■																	■										■														■	
⇒ Replacing the O-ring at the piston cooling nozzle		■	■																■										■															■
Conrod	W 8048 M0																																											
⇒ Replacing conrods		■																	■										■														■	
⇒ Replacing big-end bolts		■																	■										■															■
⇒ Replacing big-end bearing shells		■																	■										■															■
Cylinder liner	W 8049 M0																																											
⇒ Replacing a cylinder liner		■																	■										■														■	
⇒ Replacing O-rings		■																	■										■														■	
⇒ Replacing the scraper ring (if fitted)		■																	■										■														■	
Replace the crankshaft main bearings and thrust bearings	W 8050 M0																																											
⇒ Replace the lower crankshaft thrust bearing shell		■		■																									■															
⇒ Inspect the upper crankshaft thrust bearing shell and check that it is firmly seated		■		■																									■															
⇒ Replace crankshaft main bearings				■																									■															
Exhaust gas manifold	W 8051 M0																																											
⇒ Inspect the exhaust-gas collection line and insulation		■		■																																								
Pre-lubrication pump	W 8054 M0																																											
⇒ Electric motor - inspecting the brushes		■		■				■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■	■

Arbeitsschritte

		c	t	s	< 100 Oh	every 1.000 Oh	8,000 Oh	2,000 Oh	4,000 Oh	6,000 Oh	8,000 Oh	10,000 Oh	12,000 Oh	14,000 Oh	15,000 Oh	16,000 Oh	18,000 Oh	20,000 Oh	21,000 Oh	22,000 Oh	24,000 Oh	26,000 Oh	28,000 Oh	30,000 Oh	32,000 Oh	34,000 Oh	36,000 Oh	38,000 Oh	40,000 Oh	41,000 Oh	42,000 Oh	44,000 Oh	45,000 Oh	46,000 Oh	48,000 Oh	50,000 Oh	52,000 Oh	54,000 Oh	56,000 Oh	58,000 Oh	60,000 Oh		
⇒ Electric motor - inspecting the brushes	W 8054 M0	■		■								■						■						■					■								■					■	
⇒ Overhauling the pre-lubrication pump				■																																						■	
<b>Crankcase</b>	W 8061 M0																																										
⇒ Replacing O-rings			■															■											■													■	
<b>Valve clearance</b>	W 0400 M4																																										
⇒ Checking that the valves are set at an equal level								■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■
⇒ Checking valve clearance								■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■
⇒ Measuring valve stem projection								■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■
⇒ Checking the rocker cover moulded gasket								■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■
<b>Crankcase ventilation</b>	W 0507 M4																																										
⇒ Replacing the oil mist separator		■										■						■						■					■								■					■	
⇒ Replacing the blow-by hoses			■															■											■									■					■
⇒ Measuring the differential pressure								■	■	■	■	■	■	■		■	■	■		■	■	■	■	■	■	■	■	■	■		■	■		■	■		■	■	■	■	■	■	■
<b>Oil filter insert</b>	W 8038 M4																																										
⇒ Replacing the oil filter insert		■						■		■		■			■		■			■		■		■		■		■		■			■			■		■		■			■
⇒ Replacing the O-rings		■	■																																								
<b>Cylinder head</b>	W 8053 M4																																										
⇒ Replacing the cylinder head		■																						■																		■	
⇒ Replacing the rocker cover moulded gasket			■									■						■						■					■								■						■
⇒ Replacing the O-rings on the cylinder head			■																					■																			■
<b>Safety valve</b>	-----																																										
⇒ Inspect safety valve		■	■																																								
<b>Gas and smoke alarm system</b>	-----																																										
⇒ Inspect gas and smoke alarm system		■	■																																								